



Use R2/R3 only if filament supply is floating

Bias Adjust

Adjust RV1 for 1V between TP3 & TP4

R7 and RV3 values must be adjusted for V- and desired bias

Values shown are for +250V B+, -100V V-, and nominal -12V grid bias.

100-Ω resistors are grid/gate stoppers. Use 1/4W carbon comp if available, or carbon film. Exact value is not critical.

pmilett.com
6xx8 (base 9DX) Tri/Pent Driver

Tube	Pent Gm	Triode mu
6JT8	20k	100
6LY8	20k	100
6KV8	21k	70
6KR8	20k	46
6LQ8	21k	46
6LB8	20k	30
6HZ8	12.6k	70

TITLE: a2_cf

Document Number:

REV: A

Date: not saved!

Sheet: 1/1